

## Fire Alarm Bell 150mm

### Features

- Motorised Mechanism
- Universal Sound Recognition
- Diode Polarised
- Low Current Consumption
- Red Finish with FIRE Lettering

### Description

The Fire Alarm Bell is a motorised, maintenance free bell designed for fire alarm applications. Its low current consumption, ease of installation incorporating diode polarity suppression and universal recognisable bell sound, makes it an ideal choice for fire alarm installations.

Once DC power is applied to the bell, the motorised bell will operate resulting in the activation of the audible warning. Removing DC power deactivates the bell.

Cable in and out terminations are provided for ease of installation together with mountings for BESA round back box. A dedicated back box, item No 206-0006 can also be used.

The Fire Alarm Bell is available for operation on 12V d.c. and 24V d.c. fire alarm systems.



Fire Alarm Bell 150mm

### Item Numbers

Item No	Description
206-0011	Fire Alarm Bell 150mm 12V DC
206-0012	Fire Alarm Bell 150mm 24V DC
206-0006	Bell Back Box

### Specifications

Operating voltage	
201-0011	12V DC
201-0012	24V DC
Quiescent current	
201-0011	55mA
201-0012	25mA
Gong Size	150mm
Gong material / colour	Steel / Red
Housing material / colour	ABS / Red
Sound level	92dB at 1m
Dimensions	150mm Dia x 56mm H
Operating temp	-10 °C to +55 °C (no icing)
Relative humidity.	0 to 95% (non condensing)
IP rating	IP33 (indoor use)
Weight	764 grams



WORLD LEADER OF INNOVATIVE SOLUTIONS  
IN FIRE DETECTION AND ALARM SYSTEMS

**AMPAC**  
ADVANCED WARNING  
SYSTEMS

www.ampac.net

1 of 1